

TM 11-6625-665-15

DEPARTMENT OF THE ARMY TECHNICAL MANUAL

ORGANIZATIONAL, DS, GS, AND
DEPOT MAINTENANCE MANUAL

GENERATOR SIGNAL AN/USM-205



HEADQUARTERS, DEPARTMENT OF THE ARMY
MARCH 1966


OPERATING AND SERVICING MANUAL



MODEL 650A
TEST OSCILLATOR

SERIALS PREFIXED: 233-

ALSO SERIAL PREFIX 203 THRU 025



TECHNICAL MANUAL }
No. 11-6625-665-15 }

HEADQUARTERS
DEPARTMENT OF THE ARMY
WASHINGTON, DC, 1 March 1966

**Operator's, Organizational, Direct Support, General Support, and
Depot Maintenance Manual**

GENERATOR SIGNAL AN/USM-205

Section	Page
I. GENERAL DESCRIPTION _ _ _ _ _	1-1
1-1 General _ _ _ _ _	1-1
1-2 Indexes of Publications _ _ _ _ _	1-1
1-3 Forms and Records _ _ _ _ _	1-1
1-4 Reporting of Errors _ _ _ _ _	1-1
1-5 Items Comprising an Operable Equipment_ _ _ _ _	1-2
II. OPERATING INSTRUCTIONS _ _	II-1
2-1 Controls and Terminals _ _ _ _ _	II-1
2-2 Operation_ _ _ _ _	II-2
III. CIRCUIT DESCRIPTION _ _ _ _ _	III-1
3-1 Introduction_ _ _ _ _	III-1
3-2 Oscillators_ _ _ _ _	III-1
3-3 Buffer Amplifier _ _ _ _ _	III-2
3-4 AVC Amplifier _ _ _ _ _	III-2
3-5 Output Amplifier_ _ _ _ _	III-3
3-6 Output Monitor_ _ _ _ _	III-3
3-7 Output Attenuator _ _ _ _ _	III-3
3-6 Power Supply _ _ _ _ _	III-3
IV. MAINTENANCE _ _ _ _ _	IV-1
4-1 Cabinet Removal _ _ _ _ _	IV-1
4-2 Lubrication of Tuning Capaci- tor Drive Mechanism _ _ _ _ _	IV-1
4-3 Drive System for Oscillator Tuning Capacitor _ _ _ _ _	IV-1
4-4 Tube Replacement _ _ _ _ _	IV-1
4-5 Miscellaneous Test and Ad- justments_ _ _ _ _	IV-3
4-6 Complete Test Procedure _ _ _ _ _	IV-4
1) Heater and Regulated Power Supply Volt- ages _ _ _ _ _	IV-5
2) Preliminary Low Fre- quency Response Ad- justment_ _ _ _ _	IV-5
3) Low Frequency Oscilla- tor Output Voltage _ _ _ _ _	IV-5
4) Low Frequency Oscilla- tor Distortion _ _ _ _ _	IV-5
5) Low Frequency Output Distortion _ _ _ _ _	IV-6

Section	Page
6) Calibration of Low Frequency Oscillator_-----	IV-6
7) Low Frequency Oscillator Response_-----	IV-7
8) Output Meter Frequency Response Adjustment	IV-7
9) High Frequency Response Adjustment_-----	IV-7
10) High Frequency Distortion Measurement_---	IV-8
11) Check FM at 10 Mc_-----	IV-8
12) Calibration of High Frequency Oscillator_-----	IV-8
13) Calibration of X100KC Range_-----	IV-9
14) Other Adjustments_-----	IV-9
4-7 Troubleshooting_-----	IV-9
4-8 Drive Cable Replacement Procedure_-----	IV-14
V. PREVENTIVE MAINTENANCE SERVICES_-----	V-1

Appendix

II. BASIC ISSUE ITEMS LIST (BIIL) AND ITEMS TROOP INSTALLED OR AUTHORIZED LIST (ITIAL) (Not Applicable)

LIST OF ILLUSTRATIONS

Number	Page
2-1 Schematic Diagram of Output Divider Cable_-----	II-3
3-1 Block Diagram Model 650A_-----	III-0
3-2 Simplified Diagram of High Frequency Oscillator Section_-----	III-2
3-3 Simplified Diagram of High Frequency Oscillator AVC System_-----	III-2
3-4 Simplified Diagram for Power Supply Regulator_-----	III-3
4-1 Lubrication Points for Tuning Capacitor Drive Mechanism_-----	IV-2
4-2 100 Kc Filter_-----	IV-5
4-3 Calibration and Response Check for Low Frequency Oscillator_-----	IV-6
4-4 Equipment for High Frequency Distortion Measurement_-----	IV-8
4-5 Model 650A Top View_-----	IV-10
4-6 Model 650A Bottom View_-----	IV-11
4-7 Installation of Eyelets on Plastic Coated Cable_-----	IV-14
4-8 Exploded Rear View of Drive Cabling_---	IV-15
4-9 Servicing Etched Circuit Boards_-----	IV-16
4-10 Power Supply Section (Schematic)_-----	IV-17
4-11 Oscillator Section (Schematic)_-----	IV-18

LIST OF TABLES

Number	Page
4-1 Tube Complement and Function Chart _ _	IV-3
4-2 Troubleshooting_ _ _ _ _	IV-12
5-1 Replaceable Parts_ _ _ _ _	V-1

SECTION II

GENERAL DESCRIPTION

1-1. General

NOTE

Throughout this technical manual, all references to Hewlett-Packard Model 650A Test Oscillator apply to Generator, Signal AN/USM-205.

The purpose of this technical manual is to provide complete instructions for the operation, maintenance, and repair of Generator, Signal AN/USM-205. The Hewlett-Packard Model 650A Test Oscillator is a wide range precision resistance tuned oscillator covering from 10 cps to 10 mc. It has a highly stable output signal level that is adjustable from 30 microvolt to 3 volts into 600 ohms. Frequency response is essentially flat (± 1 db) throughout the complete extended range. The output impedance is normally 600 ohms. Where a low source impedance is desired, 6 ohms is provided by the Voltage Divider Cable supplied with the instrument. The Model 650A Test Oscillator output voltage is constantly monitored by a vacuum tube voltmeter at the input to the output attenuator system. This VTVM has two voltmeter scales plus a dbm scale (0 dbm = 1 milliwatt in 600 ohms). The attenuator control, in conjunction with the AMPLITUDE control, will produce a monitored signal of any desired level when the instrument is resistive loaded with 600 ohms. The flexibility and simplicity of the 650A Test Oscillator find a wide variety of uses in audio, video, rf, and alignment applications as well as laboratory wide band measurements. This instrument was designed for such applications as fast and accurate testing of filter transmission characteristics, tuned circuit response, complete receiver alignment, telephone or telegraph carrier equipment, plus video and audio amplifiers. The Model 650A Test Oscillator is

well suited as a signal source for af and rf bridge measurements. The wide range of test frequencies necessary for repair and testing of electronic frequency counters is also available from the 650A Test Oscillator.

1-2. Indexes of Publication

a. *DA Pam 310-4*. Refer to the latest issue of DA Pam 310-4 to determine whether there are new editions, changes, or additional publications pertaining to the equipment.

b. *DA Pam 310-7*. Refer to DA Pam 310-7 to determine whether there are modification work orders (MWO's) pertaining to the equipment.

1-3. Forms and Records

a. *Reports of Maintenance and Unsatisfactory Equipment*. Maintenance forms, records, and reports which are to be used by maintenance personnel at all maintenance levels are listed in and prescribed by TM 38-750.

b. *Report of Packaging and Handling Deficiencies*. Fill out and forward DD Form 6 (Report of Packaging and Handling Deficiencies) as prescribed in AR 700-58/NAVSUP PUB 378/AFR 71-4/MCO P4030.29, and DSAR 4145.8.

c. *Discrepancy in Shipment Report (DISREP) (SF 361)*. Fill out and forward discrepancy in Shipment Report (DISREP) (SF 361) as prescribed in AR 55-38/NAVSUPINST 4610.33/AFM 75-18/MCO P4610.19A, and DSAR 4500.15.

1-4. Reporting of Errors

The reporting of errors, omissions, and recommendations for improving this publication by

the individual user is encouraged. Reports should be submitted on DA Form 2028 (Recommended Changes to Publications and Blank

Forms) and forwarded direct to Commander, US Army Electronics Command, ATTN: AMSEL-MA-C, Fort Monmouth, NJ 07703.

1-5. Items Comprising an Operable Equipment

<i>FSN</i>	<i>Qty</i>	<i>Nomenclature, part No., and mfr code</i>	<i>Fig. No.</i>
6625-788-9672		Generator, Signal AN/USM-205: Frequency range 10CPS to 10 MC, 6 decade bands: calibration accuracy ±2% 10 COS to 100 KC; ±3% 100 DC to 10 MC: 3 volts RMS maximum output into 600 ohms resistive load ±1 db maximum variation throughout frequency range: output impedance 600 ohms; 300 ohms or 60 ohms when using divider, voltage MX-6122/U: Power requirements; 115/230 vac ±10%; 50 to 1,000 cps; 165 watts: overall dimensions. 20¾ in. lg x 15 in. w x 12¾ in. h which includes:	
5995-985-8214	1	Cable Assembly, Radio Frequency CG-2733/U (4 ft 0 in.)	2-1
6625-759-7436	1	Divider, Voltage MX-6122/U	